



IN ADMIRATION OF MUSIC

# MENTOR SUB

Despite its deceptive simplicity of purpose – to reproduce only the bottom two or three octaves, a subwoofer actually offers many challenges in installation and set-up, before it can achieve smooth in-room response and seamless integration with your main speakers.

To make your task easier, DALI MENTOR SUB features a dedicated remote control that allows you to adjust level, crossover frequency and phase from your favourite listening position, instead of crouched down behind the subwoofer. The remote also controls Mute and Power On/Off. Convenient Auto-switching turns the unit on when a signal is detected and off again after a period of silence.

Driven by a 500 Watt Class D amplifier, the powerful 10" long-stroke driver is downward-firing for improved acoustic coupling to the room and placement closer to walls without compromising performance.



## SPECIFICATIONS

Frequency range (+/- 3dB) [Hz]:	25,0 - 250,0
Maximum SPL [dB]:	111,0
Crossover frequencies:	40-120
Low frequency driver:	Paper fibre cone
Enclosure type:	Closed box
Max. Amplifier Power Output [W]:	500
Continuous IEC Power Output [W]:	300
Maximum power consumption [W]:	450
Connection input(s):	Mono "line level" (LFE);S
Input impedance [kOhm]:	2
Functions:	Volume (gain);Crossover f
Recommended placement:	Floor
Loudspeaker type:	Subwoofer
Magnetic shielding:	No
Max loudspeaker dimensions incl. base and grille	365 X 330 X 340

Loudspeaker weight including base and grille [kg]: 22,4

## AVAILABLE FINISHES



Cherry

White

Black